

FMI501201

Power	130	W
Supply voltage	48	V
RMS Current	2.7	A
Rated Torque	200	mNm
Peak Torque	500	mNm
Rated speed	6000	rpm
Speed const Kv	130	rpm/V
Torque const Kt	74	mNm/A
Motor const	67	mNm/vW
Terminal resistance	0.8	Ω
Terminal inductance	500	μH
Number of pole pairs	7	
Max. efficiency	89.1%	
Rotor inertia	0.22	kgcm^2
Weight	105	g
Winding type	Y	

20/11, Olshevskogo str., Suite 22
Minsk, 220073, Belarus
+375 (33) 376 04 60 | sales@rozum.com | www.rozum.com

